HOWNER_OPERATOR2

English Name	EPA Handler ID **(Primary Key)**
Description	Unique RCRA identification number assigned by the implementing State or Region to each RCRA site (e.g., generators; transporters; and treatment, storage, disposal facilities).
Data Type and Length	CHAR (12)
Allowed Values	Valid ID as outlined below: The ID can be a minimum of 4 characters and a maximum of 12 characters. The first two characters must be a valid state postal code which corresponds to the state in which the handler is located. Spaces are not allowed.
Default Value	
Notes	Handlers associated with Navajo Nation should be assigned Handler IDs beginning with "NN" regardless of where the handler is physically located.

English Name	Activity Location **(Primary Key)**
Description	Indicates the location of the agency regulating the handler.
Data Type and Length	CHAR (2)
Allowed Values	State postal code
Default Value	Location associated with the current user ID.
Notes	For a list of valid state postal codes, refer to the Column Information Report for LU_STATE.

English Name	Source Type **(Primary Key)**
Description	Code indicating the source of information for the associated data (activity, wastes, etc.).
Data Type and Length	CHAR (1)
Allowed Values	A — Part A B — Annual/Biennial Report updated with Notification E — Emergency I — Implementer N — Notification R — Annual/Biennial Report T — Temporary
Default Value	

English Name	Handler Sequence Number **(Primary Key)**
Description	Sequence number for each source record about a handler.
Data Type and Length	NUMBER (6.0)
Allowed Values	1 - 999999
Default Value	

HOWNER_OPERATOR2

English Name	Owner/Operator Sequence Number **(Primary Key)**
Description	Sequential number used to order multiple occurrences of owners and operators.
Data Type and Length	NUMBER (4.0)
Allowed Values	1 - 9999
Default Value	
Notes	This number will be incremented by one for each Add transaction.

English Name	Owner/Operator Indicator
Description	Code indicating whether the data is associated with a current or previous owner or operator. The system will allow multiple current owners and operators.
Data Type and Length	CHAR (2)
Allowed Values	CO Current owner CP Current operator
Default Value	

English Name	Owner/Operator Name
Description	Owner Name: The name of the entity (individual, agency, corporation) having legal ownership of the physical operation. The owner name may or may not be the same as the actual site name or the operator name. Operator Name: The name of the entity (individual, agency, corporation) that is responsible for the overall operation of the facility. The operator name may or may not be the same as the actual site name or the owner name.
Data Type and Length	VARCHAR2 (40)
Allowed Values	Any non-blank value
Default Value	

English Name	Owner/Operator Type
Description	Owner Type: Code indicating the type of entity that legally owns the facility. Operator Type: Code indicating the type of entity that is responsible for the overall operation of the facility.
Data Type and Length	CHAR (1)
Allowed Values	C County D District F Federal I Indian M Municipal O Other P Private S State
Default Value	

HOWNER_OPERATOR2

English Name	Date Became Current
Description	Date indicating when the owner/operator became current.
Data Type and Length	DATE
Allowed Values	Valid date in MM/DD/YYYY format
Default Value	

English Name	Date Ended Current
Description	Date indicating when the owner/operator changed to a different owner/operator.
Data Type and Length	DATE
Allowed Values	Valid date in MM/DD/YYYY format
	blank Not provided
Default Value	blank
Notes	When entering a new owner/operator, any previous owners/operators that are no longer current should be updated to include a Date Ended Current.

English Name	Owner/Operator Street 1
Description	First line of the street address or post office box number of the facility owner or operator.
Data Type and Length	VARCHAR2 (30)
Allowed Values	Any value
	blank Not provided
Default Value	blank

English Name	Owner/Operator Street 2
Description	Second line of the street address or post office box number of the facility owner or operator.
Data Type and Length	VARCHAR2 (30)
Allowed Values	Any value
	blank Not provided
Default Value	blank

HOWNER_OPERATOR2

English Name	Owner/Operator City
Description	The city or town in the address of the facility owner or operator.
Data Type and Length	VARCHAR2 (25)
Allowed Values	Any value
	blank Not provided
Default Value	blank

English Name	Owner/Operator State
Description	The two-letter postal code for the state in the address of the facility owner or operator.
Data Type and Length	CHAR (2)
Allowed Values	Valid state postal code
Default Value	
Notes	For a list of valid state postal codes, refer to the Column Information Report for LU_STATE.

English Name	Owner/Operator Country
Description	The country code for the address of the facility owner or operator.
Data Type and Length	CHAR (2)
Allowed Values	For a complete list of valid country codes, refer to: http://www.bcpl.net/~j1m5path/isocodes.html.
	Valid country code
Default Value	US - United States

English Name	Owner/Operator Zip Code
Description	Zip code in the address of the owner or operator.
Data Type and Length	VARCHAR2 (14)
Allowed Values	Any value
	blank Not provided
Default Value	blank

HOWNER_OPERATOR2

English Name	Owner/Operator Phone
Description	Telephone number associated with the owner or operator.
Data Type and Length	VARCHAR2 (15)
Allowed Values	Any value
	blank Not provided
Default Value	blank
Notes	Telephone number can include space, parentheses and hyphen.

English Name	Dunn & Bradstreet Number
Description	Nine-digit unique identification number assigned by the Dunn & Bradstreet organization to a company that might own or operate a site. The identifier serves as linkage for commercially available information pertaining to the site.
Data Type and Length	VARCHAR2 (10)
Allowed Values	Any value
	blank Not provided
Default Value	blank

English Name	Owner/Operator Street Number
Description	The street number from the address of the facility owner or operator.
Data Type and Length	VARCHAR2 (12)
Allowed Values	Any value
	blank Not provided
Default Value	blank

English Name	User ID of Last Change
Description	Records the user ID of the last person to change the data.
Data Type and Length	VARCHAR2 (6)
Allowed Values	Valid user ID
Default Value	Current user ID

HOWNER_OPERATOR2

English Name	Date of Last Change
Description	Records the date that the data was last changed.
Data Type and Length	DATE
Allowed Values	Valid date/time stamp
Default Value	Current date and time

English Name	Notes
Description	Additional information regarding the owner/operator.
Data Type and Length	VARCHAR2 (240)
Allowed Values	Any value
	blank Not provided
Default Value	blank

* End of Report *